

# PRODUCT SPECIFICATION SHEET

**Product Name: P4460 Kill A Watt™ EZ Electricity Usage Monitor**

| Function                        | Range           | Accuracy Typ. | Accuracy Max. |
|---------------------------------|-----------------|---------------|---------------|
| RMS Voltage                     | 85-125 Vrms     | 0.2%          | 1%            |
| RMS Current                     | 0.00~15.00 Arms | 0.3%          | 1%            |
| Active Power                    | 0~1875 Watt     | 0.5%          | 2%            |
| Apparent Power                  | 0~1875 VA       | 0.5%          | 2%            |
| Line Frequency                  | 47.0~63 Hz      | 0.1 Hz        | 2%            |
| Power Factor                    | 0.00~1.00       | 0.01          | 0.03          |
| Power Quantity                  | 0.00~9999 KWH   | 0.5%          | 2%            |
| Time Quantity                   | 00:00~9999      | 30ppm         |               |
| Display Update                  | 1 Sec           | -             |               |
| Power Consumption               | 10 Wmax         | -             |               |
| Typical: V=90V~125V, A=0.2A~15A |                 |               |               |

| Model | Operating Voltage | Max Voltage          | Max Current | Max Power | Weight | Dimensions                   |
|-------|-------------------|----------------------|-------------|-----------|--------|------------------------------|
| P4460 | 115 VAC           | 125 VAC<br>50 / 60Hz | 15A         | 1875 VA   | 5 oz.  | 5-1/8" H x 2-1/2" W x 1-1/2" |